



Quick Connect Guide

D2iP IP Output Monitors

Models: VZ-215D2iP / VZ-42D2iP

Default Settings:

IP Address: 10.20.30.40
Subnet Mask: 255.255.255.0
Default Gateway: 10.20.30.1
Username: root
Password: root

Each ViewZ IP Public View Monitor comes packaged with a CD containing our free **SmartViewer** and **IP Installer** software applications.

Smartviewer: Self-executable file that installs codecs and drivers required by Internet Explorer for viewing on browser.

IP Installer: ViewZ IP utility that searches for all ViewZ devices on a physical network by mac address.

INSTALLATION

- ① Turn off your PC's wireless device
- ② Load the **CD** in your PC (Microsoft .NET 2.0 Framework is required)
- ③ Double Click **IP Installer_Setup_V3.3.0** then follow the prompts
- ④ Double Click **SmartViewer.exe_V1.15.0.0** to auto install support files

CONFIGURATION

- ① From your desktop, open **IP Installer** application
- ② Scan network by clicking on the magnifying glass
- ③ Right click a device to enter Manual IP Setup
- ④ Change **Server Name** to your preference
- ⑤ Check **HTTP Port** and set up as 80 (Inner Port)
- ⑥ Set up as **Static** address and enter preferred network addresses
- ⑦ Insert Admin Password then select **SET** to save new IP address

*Note – IP Installer will not indicate if your password is incorrect, verify password is correct before clicking **Set**

Sales & Tech Support: 1-888-99-ViewZ (84399)

www.ViewZusa.com